

## AOM Driver 97-03926-12 (20-160MHz, 3.2W, 8 channels)

AODS Synth DDS 8 CH

### General Features

- 8 channels, combined as composite output.
- On-board composite output power measurement.
- Independent linear amplitude modulation on each channel.
- Common blanking signal for all channels.
- Independent frequency shift modulation on each channel.
- Robust command set.
- Built in Network Protocols (i.e. Point to Point Protocol PPP, Link Control Protocol LCP, Password Authentication Protocol PAP, Internet Control Message Protocol, etc.)
- Control Voltage Levels: RS232.

### Specifications

Part code	160T2-8SAR-24-3.2B
Frequency specifications	
Frequency range	20-160MHz
Frequency resolution (1)	0.1Hz
Frequency stability	+/-2 ppm/deg C
Frequency preload time (2)	<8 us
Frequency toggle time (3)	<80ns
Amplitude Specifications	
RF output power	3.2W
RF output power, per channel	0.4W
Modulation bandwidth (4)	>2MHz
Dynamic range (5)	>35dB
Intermodulation (6)	>41dB
Spurious	>45dBc
Signal to noise ratio (7)	>75dB
Interfaces	
RF output impedance	50 Ohms
Amplitude modulation input level	0-10V
FSK modulation input level	3.3V
Blanking input level	3.3V
Digital controls	ASCII
Sensor input	+/-3.3V
Power input, from DC supply	24V@2A
Dimension	165x132x25mm

### Remarks:

1. Actually 0.0931 Hz, closest approximation to set frequency will be chosen.
2. Typically 1-8  $\mu$ s, each frequency requires 32 bits, plus a starting RAM address.
3. Direct switch mode to one of three preset frequency.
4. Measured at -3 dB point, DC coupled.
5. 20-160 MHz.
6. 2 tone test, 100 MHz + 105 MHz, each of 125 mW output
7. 1 MHz measurement bandwidth, 125 mW reference tone.
8. Reference Outline Drawing 97-03926-12-15.

**Modulation and FSK/Blank Connector Pin out**

Pin	Function	Direction	Description	Pin	Function	Direction
1	VCC24	-	-	21	VCC24	-
2	VCC24	-	-	22	GND	-
3	GRD	-	-	23	FSK0	-
4	GND	-	-	24	FSK1	-
5	GND	-	-	25	FSK2	-
6	GND	-	-	26	FSK3	-
7	GND	-	-	27	FSK4	-
8	GND	-	-	28	FSK5	-
9	GND	-	-	29	FSK6	-
10	GND	-	-	30	FSK7	-
11	GND	-	-	31	BLANK	-
12	GND	-	-	32	GRD	-
13	MOD 0	-	-	33	MOD 0+	-
14	MOD 1-	-	-	34	MOD 1+	-
15	MOD 2-	-	-	35	MOD 2+	-
16	MOD 3-	-	-	36	MOD 3+	-
17	MOD 4-	-	-	37	MOD 4+	-
18	MOD 5-	-	-	38	MOD 5+	-
19	MOD 6-	-	-	39	MOD 6+	-
20	MOD 7-	-	-	40	MOD 7+	-

